

increased safety



Signalling components, switch handles and electrical functions

Indicators:

- Mounting on door (supplied with coloured indicator lens)
Multi LBD AC 24 V, 48 V, 110 V, 230 V, DC 24 V, 48 V
– Equipped either with a terminal block (clamping capacity twice 2 x 2.5mm²) or with a cable outlet (3 m, 2 x 0.75 mm²) suitable for mounting on non Ex enclosure for cable outlets

	Weight (Kg)	Volume (dm ³)	Cat. No. with terminal block	Cat. No. with cable	Pack
Red indicator	0.10	0.10	0982 11	0982 21	1
Green indicator	0.10	0.10	0982 12	0982 22	1
White indicator	0.10	0.10	0982 10	0982 20	1
Yellow indicator	0.10	0.10	0982 14	0982 24	1
Blue indicator	0.10	0.10	0982 13	0982 23	1

Changeover selector switch

Connection via 2 x 2.5 mm² terminals

Single pole I - II (switch handle 0988 51 not supplied)	0.2	0.4	0988 53	1
Single pole with stop I - 0 - II (switch handle 0988 51 not supplied)	0.2	0.4	0988 54	1

16A switch

Double pole I - II (switch handle 0988 51 not supplied)	0988 55
---	---------

Padlockable handle for selector switch, changeover switch and 16 A switch

Supplied with fixing base	0.09	0.4	0988 51	1
---------------------------	------	-----	---------	---

4-pole control and load break switches

(switch handle 0986 66 not supplied)

Control switch 4 NO - 2 positions	0.2	0.10	0988 21	1
Control switch 2 NO + 2 NC - 2 positions	0.2	0.10	0988 22	1
Control switch 1 NC + 3 NO - 2 positions	0.2	0.10	0988 23	1
Control switch 3 NC + 1 NO - 2 positions	0.2	0.10	0988 24	1
Control switch 1 NO - 4 positions	0.2	0.10	0988 25	1
Control switch - 3 positions	0.2	0.10	0988 26	1
Control switch - 3 positions	0.2	0.10	0988 27	1
Control switch - 3 positions	0.2	0.10	0988 28	1
with automatic return from II to I				
Control switch - 3 positions	0.2	0.10	0988 29	1
with automatic return from II to 0				
Control switch - 5 positions	0.2	0.10	0988 30	1
Load break switch 4 NO - 2 positions	0.2	0.10	0988 31	1
Load break switch 3 NO + 1 NC - 2 positions	0.2	0.10	0988 32	1

Rotary switch handle for 4-pole switch

- Supplied with fixing base for mounting on door
- Can be used for any of the 4-pole switch functions

0986 66 1

Part number in bold : fast moving references

Zone 1 & 2 - 21 & 22	ATEX	CEI	II 2 G/D ou II 2 G
EExe II ou EEx de IIC			

TECHNICAL DATA

- Components conforming to Directive 94/9 EC, standards EN 50014/18/19/28

- Contact and signalling components

Zones: 1 and 2 and 21 - 22

- Approved type: AUX

- According to CENELEC: 0081 II 2 G/D EEx ed IIC or EEx e II

LCIE: 00 ATEX 0002 U

- According to IEC: Ex ed IIC or Ex e II

LCIE: Ex 00.012 U

- According to UL: AEX ed IIC or AEX e II

UL: E 214068

- Selector switches, changeover switches and 16 A switches

Zones 1 and 2 authorised in an approved dustproof enclosure

- Approved type: 8008/2

- According to CENELEC: II 2 G EEx de IIC T6

PTB 00 ATEX 1111 U

Operating temperature - 55°C to + 40°C

- 4-pole control and load break switches

Zones 1 and 2 authorised in an approved dustproof enclosure

- Approved type: 07-3331-1

- According to CENELEC: II 2 G EEx de IIC T6

PTB 99 ATEX 1043 U

Operating temperature - 50°C to + 60°C

- According to UL UL: E 184198

Operating temperature - 35°C to + 60°C

- Padlockable handle (0988 51)

- Approved type: AUXe

- 03 ATEX 0012U (CENELEC)

- Ex 03.011U (IEC)

IP66 protection index (for actuators, indicator units and switch handles)

Dimensions (mm) :

0982 10/11/12/13/14

